HD/SD-SDI DIGITAL DISTRIBUTION AMPLIFIER DiaiFlex 1132





FEATURES

m Composite & Component SDI

m SMPTE 259M, 344M, 292M compliant

m Serial Digital Input

m HD Input

m Eight or Four Serial Outputs

m Fault Indication

m Automatic Equalization and Re-clocking

Mounting Frame Options

1000 - Single Power Supply, Holds 11 Modules 1000/2 - Dual Power Supply, Holds 10 Modules

7200 - Mounting Frame, Holds 1 Module

The LINK 1132 DigiFlex serial distribution amplifier restores the incoming signal to its proper amplitude. The signal is reshaped with automatic equalization, and DC restoration. The 1132 's maximum equalized length for cable for SD is 300m at 270Mb/s, and for HD, 100m at 1.485Gb/s. Eight outputs are provided on a removable rear cell 1033, and four outputs are provided on the 1032 rear cell. An LED at the front edge of the front module, and one on the rear module indicate a Loss of Signal.

A rear I/O module must be selected for the specific front signal module. The signal module and rear I/O module with the flexibility of the frame place virtually no limits on the versatility of the DigiFlex 1000 system.

The input signal can be 143Mb/s, 177Mb/s, 270Mb/s, 360Mb/s, 540Mb/s, and 1.4835/1.485Gb/s standards. The front module has LED's that tell if the input signal has locked, and the data rate that it is locked.

The 1000 series DigiFlex modules are compact designs that allow eleven modules to mount in the 1000 frame and ten modules with a redundant power supply. Any 1000 series module will operate in the 1000 frame in any configuration, audio or video, digital/analog, generators or test modules.

Backed by Link's 10-year warranty, the 1132 will provide years of outstanding performance.

DIGIFLEX 1132 SERIAL DIGITAL DISTRIBUTION AMPLIFIER

SERIAL DIGITAL VIDEO INPUT:
Number of Inputs:
Connectors: BNC
Standards:
Composite SDI:
SD SDI:
SD HD:
Impedance:
Return Loss: >15dB
Signal Level 800mV ± 10%
Input Cable Length Max:
SD:
HD:
DIGITAL OUTPUTS:
Number of Outputs:
Connectors: BNC
Standards: Same as input
Impedance:
Return Loss:
Signal Level:
Rise & Fall Time:
SD:
HD:
Overshoot: 8% of Amplitude
Additive Jitter:
SD at 270Mb/s:
HD at 1.485Gb/s:
ть ист. 1000 б р р, сургал
FRONT MODULE INDICATORS:
Lock Detect: Green LED
Loss of Signal:
SD: Green LED
HD:
Data Rates:
Cable Length Indicator: Only used for SMPTE 259M standards, Green LED(4)
ENVIRONMENTAL:
Temperature:
Humidity:
Power:

MECHANICAL:

Height:.....3.2 Inch Width:.....1.0 Inch Depth:.....10 Inch Weight:.....7.25 Oz

PROFESSIONAL SERIES-modular system products--by LINK 1032 Rear Cell I/O 0. HD Input 1. HD Out 2 HD Out 3. HD Out 4. HD Out



1033 REAR Rear Cell I/O 0. HD Input 1. HD Out 2. HD Out 3. HD Out 4. HD Out 5. HD Out 6. HD Out 7. HD Out 8. HD Out



1033 REAR



1032 REAR